

General Description

CapSense Megacell is a scalable capacitive sensor signal conditioning circuit IP.

It can be used for intelligent push-button sensors e.g. for remote controls.

The capacitance increases with the touch of the button by a factor depending on the sensor material (e.g. $3 * C_{\text{sensor}}$). It has all necessary column driving circuitry as well as row readout amplifiers, filters and ADC circuitry. The sensor array itself can be a flexible polymer based sensor array with a resolution as high as 500dpi. A column driver drives a sine wave signal coming from an integrated signal generator while all other columns are tight to virtual ground. All rows are then scanned at the same time. The value is filtered and converted into a digital signal. The result can be read out through a parallel bus at a resolution of 8 bit. The controller sequence allows to scan a whole sensor field several times a second, depending on matrix size, frequency and the single push button/sensor field capacitance. The circuit system is highly flexible (CMOS06, BiCMOS035) and can be designed into any ASIC requirement.

Ratings, Parameters and Conditions


Parameter / Condition	Symbol	Min	Typ.	Max	Unit	Comment
Electrical Parameters						
Sensor Array						
CapSense Array size	N_{array}	2x2		100x100		Can be either pixels or touch buttons
Sensor capacitance	C_{sensor}	3		1000	fF	adjustable to any sensor field
Pixel clock	F_{pixel}		7.3728		MHz	representative value/adjustable
Line sync clock	F_{line}		7.2		kHz	representative value/adjustable
Frame sync clock	F_{frame}		8.44595		Hz	representative value/adjustable
Row Signal Amplifier Unit						
settling time	t_{START}			8	us	
counter delay	t_{DZ}			2	ns	after clock posedge
reset delay	t_{R}			2	ns	after reset negedge
data preload time	t_{DT}	2			ns	
data hold time	t_{DH}	2			ns	
filter time constant	T_{FILT}		1000		ns	analog row filter
bandwidth I/U converter	$BW_{\text{I/U}}$	10			MHz	determines array frequency
Column Driver Unit						
linear range column driver	V_{shift}	1		4	V	
shift frequency	f_{shift}		10		kHz	column to column
Stimuli clock frequency	F_{stim}	1	10	12	MHz	

IO-Description

Interface	I/O	Function	Comment
Vdd	Input	Supply	
Gnd	Input	Supply	
Array_c[0..n]	Output	driver	Array columns
Array_r[0..n]	Input	readout	Array rows
clk	Input	Clock	
reset	Input	Reset	Global reset
ena	Input	Enable	
D_out[0..7]	Output	Data	Output data
Setup[0..2]	In/out	Serial port	Progr./Test register

For more information please contact
PE GmbH at:
info@pe-gmbh.com

Symbol and external Component Schematic



or visit our web site at:
www.pe-gmbh.com



Dieses Projekt wird mit Mitteln des Europäischen Sozialfonds (ESF) gefördert. Es erzeugt einen gemeinschaftlichen Mehrwert „Investition in Ihre Zukunft“.